## CCT Mode

**Slider** Legend

Not Active, Not Editable
Active, Not Editable
Active, Editable

**CCT** Legend

Not Active, Not Editable (CCT, Hue, and Sat)
Active, Not Editable (CCT, Hue, and Sat)
Active, Editable (CCT, Hue, and Sat)

CCT MODE Default Screen, INTENSITY is Active and Not Editable

1



Press Encoder to make INTENSITY Active and Editable.
Rotate Encoder to Adjust INTENSITY Level.

2



Press Encoder to navigate to CCT (Active and Not Editable).

3



Press Encoder to make CCT Active and Editable.
Rotate Encoder to Adjust CCT Level.

4

Press Encoder to navigate to GRN-MAG (Active and Not Editable).

5

Press Encoder to make GRN-MAG Active and Editable.
Rotate Encoder to Adjust GRN-MAG Level.

6

## Gel Mode

**Slider** Legend

Not Active, Not Editable
Active, Not Editable
Active, Editable

**Gel Swatch** Legend

Not Active, Not Editable (CCT, Hue, and Sat)
Active, Not Editable (CCT, Hue, and Sat)
Active, Editable (CCT, Hue, and Sat)

GEL MODE Default Screen, INTENSITY is Active and Not Editable

1



Press Encoder to make INTENSITY Active and Editable.
Rotate Encoder to Adjust INTENSITY Level.

2

Press Encoder to navigate to CCT (Active and Not Editable).

3

Press Encoder to make CCT Active and Editable.
Rotate Encoder to Adjust CCT Level.

4

Press Encoder to navigate to HUE (Active and Not Editable).

5

Press Encoder to make HUE Active and Editable.
Rotate Encoder to Adjust HUE Level.

6

Press Encoder to navigate to SAT (Active and Not Editable).

7

Press Encoder to make SAT Active and Editable.
Rotate Encoder to Adjust SAT Level.

8

< PAGE and PAGE > Will Quickly Navigate Between GEL Pages.

## HSI Mode

**Slider** Legend

Not Active, Not Editable
Active, Not Editable
Active, Editable

**Color Wheel** Legend

Not Active, Not Editable (Hue and Sat)
Active, Not Editable (Hue and Sat)
Active, Editable (Hue and Sat)

HSI MODE Default Screen, INTENSITY is Active and Not Editable

1



Press Encoder to make INTENSITY Active and Editable.
Rotate Encoder to Adjust INTENSITY Level.

2

Press Encoder to navigate to HUE (Active and Not Editable).

3

Press Encoder to make HUE Active and Editable.
Rotate Encoder to Adjust HUE Level.

4



Press Encoder to navigate to SAT (Active and Not Editable).

5

Press Encoder to make SAT Active and Editable.
Rotate Encoder to Adjust SAT Level.

6

## XY Mode

**Slider** Legend

Not Active, Not Editable
Active, Not Editable
Active, Editable

**Chromaticity Diagram** Legend

Not Active, Not Editable (X and Y)
Active, Not Editable (X and Y)
Active, Editable (X and Y)

XY MODE Default Screen, INTENSITY is Active and Not Editable

1

Press Encoder to make INTENSITY Active and Editable.
Rotate Encoder to Adjust INTENSITY Level.

2



Press Encoder to navigate to X (Active and Not Editable).

3

Press Encoder to make X Active and Editable.
Rotate Encoder to Adjust X Level.

4

Press Encoder to navigate to Y (Active and Not Editable).

5

Press Encoder to make Y Active and Editable.
Rotate Encoder to Adjust Y Level.

6

## RGBACL Mode



**Slider** Legend

Not Active, Not Editable
Active, Not Editable
Active, Editable

RGBACL MODE Default Screen, INTENSITY is Active and Not Editable

1



Press Encoder to make INTENSITY Active and Editable.
Rotate Encoder to Adjust INTENSITY Level.

2



Press Encoder to navigate to R (Active and Not Editable).

3



Press Encoder to make R Active and Editable.
Rotate Encoder to Adjust R Level.

4



Press Encoder to navigate to G (Active and Not Editable).

5



Press Encoder to make G Active and Editable.
Rotate Encoder to Adjust G Level.

6

Press Encoder to navigate to B (Active and Not Editable).

7



Press Encoder to make B Active and Editable.
Rotate Encoder to Adjust B Level.

8



Press Encoder to navigate to A (Active and Not Editable).

9



Press Encoder to make A Active and Editable.
Rotate Encoder to Adjust A Level.

10

Press Encoder to navigate to C (Active and Not Editable).

11



Press Encoder to make C Active and Editable.
Rotate Encoder to Adjust C Level.

12

Press Encoder to navigate to L (Active and Not Editable).

13

Press Encoder to make L Active and Editable.
Rotate Encoder to Adjust L Level.

14

< PREV and NEXT > Will Quickly Navigate to the Previous or Next selection if the current selection is Active and Editable.

## SOURCE Mode

**Slider** Legend

Not Active, Not Editable
Active, Not Editable
Active, Editable

**Category** Legend




Not Selected
Selected
Activated

Lorem ipsu

SOURCE MODE Default Screen, INTENSITY is Active and Not Editable

1



Press Encoder to make INTENSITY Active and Editable.
Rotate Encoder to Adjust INTENSITY Level.

2



Press and Rotate Encoder to Navigate to Desired SOURCE MODE.

3

Press Encoder to Activate the Selected SOURCE.

4

To Select Additional SOURCES, Press and Rotate Encoder to Navigate.

5



Press Encoder to Activate the Selected SOURCE.

6

## PRESETS



**Preset** Legend



Not Selected
Selected
Activated

PRESETS Default Screen, Top PRESET is Selected, Not Active

1



Press Encoder to Activate the Selected PRESET.

2

Press and Rotate Encoder to Navigate to the Desired PRESET.

3



< PAGE and PAGE > Will Quickly Navigate to the Previous or Next Page.

## MENU

**Menu** Legend

Not Selected
Selected
Activated

MENU Default Screen, Top Item is Selected, Not Active

1



Rotate Encoder to Navigate to the Desired MENU Item.

2



Press Encoder to Activate the Desired MENU Item.

3



## MENU > DMX

**MENU > DMX** Legend

Not Selected
Selected
Activated

MENU>DMX Default Screen, Top Item is Selected, Not Active

1



Rotate Encoder to Navigate to the Desired MENU>DMX Item.

2



Press Encoder to Activate the Desired MENU>DMX Item.

3



## DIALOG SCREEN 1

## DIALOG SCREEN 2